

DC Electronic Load

PROGRAMMABLE, HIGH PRECISION

PPL SERIES

150V / 500V

15A / 30A / 60A / 120A

150W / 300W / 600W



FEATURES

- 4 basic functions: CC, CV, CR, CP
- 9 basic operation modes: CCL, CCH, CVL, CVH, CRL, CRM, CRH, CPV, CPC
- 24-bit A/D converter and 16-bit D/A converter, 40kHz D/A conversion speed, high resolution & high speed
- Hardware circuit for CR function, faster transient response and higher CR accuracy
- High speed transient test function, max. test frequency 2kHz
- Over current, over voltage, over power, over temperature and reverse voltage protections
- 4.3-inch backlit Segment LCD display
- High speed rotary dial and keypad input
- Auto ON/OFF function
- List Mode function, step 10ms-99999s, free to set numbers of cycles and to be linked to other lists
- Auxiliary functions: short circuit test, battery discharge capacity test
- Save & recall function for frequently used setups
- Intelligent cooling system, ensure high stability during long-time operation under full load
- Standard RS-232 interface, support SCPI commands, support Labview
- Optional RS-232 to USB cable

Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-38-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06

Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (6552)20-53-41
Нижний Новгород (831)429-08-12
Новоузенец (3843)20-46-81
Новосибирск (383)227-86-73
Омск (381)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Казахстан (772)734-952-31

Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Таджикистан (992)427-82-92-69

Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4882)69-52-93

DC Electronic Load

PROGRAMMABLE, HIGH PRECISION

SPECIFICATIONS

| Model | PPL-8611C2 | PPL-8612C2 | PPL-8612C3 | PPL-8612B1 | PPL-8613C3 | PPL-8613C4 | PPL-8613B2 |
|--|-------------------|-------------|-------------|------------|------------|-------------|------------|
| Rated input (0°C~40°C) | | | | | | | |
| Voltage | 0~150V | 0~150V | 0~150V | 0~500V | 0~150V | 0~150V | 0~500V |
| Current | 1mA~30A | 1mA~30A | 1mA~60A | 1mA~15A | 1mA~60A | 1mA~120A | 1mA~30A |
| Power *1 | 150W | 300W | 300W | 300W | 600W | 600W | 600W |
| MOV@FS current | 1.5V | 0.82V | 1.2V | 3.8V | 0.9V | 1.6V | 4.2V |
| Constant voltage mode (CV) | | | | | | | |
| Low range (CVL) | 0.1~30V | 0.1~30V | 0.1~30V | 0.1~30V | 0.1~30V | 0.1~30V | 0.1~30V |
| Resolution | 1mV | 1mV | 1mV | 1mV | 1mV | 1mV | 1mV |
| Accuracy | ±(0.05%+0.02%FS) | | | | | | |
| High range (CVH) | 0.10~150V | 0.10~150V | 0.10~150V | 0.10~500V | 0.10~150V | 0.10~150V | 0.10~500V |
| Resolution | 10mV | 10mV | 10mV | 10mV | 10mV | 10mV | 10mV |
| Accuracy | ±(0.05%+0.025%FS) | | | | | | |
| Constant current mode (CC) | | | | | | | |
| Low range (CCL) | 0~3A | 0~3A | 0~6A | 0~1.5A | 0~6A | 0~12A | 0~3A |
| Resolution | 1mA | 1mA | 1mA | 1mA | 1mA | 1mA | 1mA |
| Accuracy | ±(0.1%+0.1%FS) | | | | | | |
| High range (CCH) | 0~30A | 0~30A | 0~60A | 0~15A | 0~60A | 0~120A | 0~30A |
| Resolution | 10mA | 10mA | 10mA | 10mA | 10mA | 10mA | 10mA |
| Accuracy | ±(0.1%+0.15%FS) | | | | | | |
| Constant resistance mode (CR) (Input voltage /current≥10%FS) | | | | | | | |
| Low range (VH CRL) | ≈0.06~6Ω | ≈0.04~6Ω | ≈0.025~3Ω | ≈0.3~36Ω | ≈0.02~3Ω | ≈0.015~1.5Ω | ≈0.15~18Ω |
| Resolution | 100uΩ | 100uΩ | 50uΩ | 600uΩ | 50uΩ | 25uΩ | 300uΩ |
| Accuracy (Impedance) | ±(0.5%+0.5%FS) | | | | | | |
| Middle range (VH CRM) | ≈6~600Ω | ≈6~600Ω | ≈3~300Ω | ≈36~3600Ω | ≈3~300Ω | ≈1.5~150Ω | ≈18~1800Ω |
| Resolution | 2.7us | 2.7us | 5.4us | 0.45us | 5.4us | 10us | 0.90us |
| Accuracy (Conductance) | ±(1%+1%FS) | | | | | | |
| High range (VH CRH) | ≈60~4000Ω | ≈60~4000Ω | ≈30~4000Ω | ≈360~4000Ω | ≈30~4000Ω | ≈150~4000Ω | ≈180~4000Ω |
| Resolution *2 | 0.30us | 0.30us | 0.20us | 0.051us | 0.20us | 1.2us | 0.10us |
| Accuracy (Conductance) | ±(1.5%+1.5%FS) | | | | | | |
| Low range (VL CRL) | ≈0.06~1.12Ω | ≈0.04~1.12Ω | ≈0.025~0.6Ω | ≈0.3~2.4Ω | ≈0.02~0.6Ω | ≈0.015~0.3Ω | ≈0.15~1.2Ω |
| Resolution | 18uΩ | 18uΩ | 9.6uΩ | 38uΩ | 9.6uΩ | 4.8uΩ | 19uΩ |
| Accuracy (Impedance) | ±(0.5%+0.5%FS) | | | | | | |
| Medium range (VL CRM) | ≈1.12~112Ω | ≈1.12~112Ω | ≈0.6~60Ω | ≈2.4~240Ω | ≈0.6~60Ω | ≈0.3~30Ω | ≈1.2~120Ω |
| Resolution | 15us | 15us | 27us | 6.8us | 27us | 54us | 14us |
| Accuracy (Conductance) | ±(1%+1%FS) | | | | | | |
| High range (VL CRH) | ≈11.2~2000Ω | ≈11.2~2000Ω | ≈6.0~2000Ω | ≈24~2000Ω | ≈6.0~2000Ω | ≈3.0~2000Ω | ≈12~2000Ω |
| Resolution | 1.6us | 1.6us | 3.0us | 0.78us | 3.0us | 6.1us | 1.5us |
| Accuracy (Conductance) | ±(1.5%+1.5%FS) | | | | | | |
| Constant power mode (CP) (Input voltage /current≥10%FS) | | | | | | | |
| Range | 0~150W | 0~300W | 0~300W | 0~300W | 0~600W | 0~600W | 0~600W |
| Resolution | P<100W | 1mW | 1mW | 1mW | 1mW | 1mW | 1mW |
| | P≥100W | 10mW | 10mW | 10mW | 10mW | 10mW | 10mW |
| Accuracy | ±(1%+0.1%FS) | | | | | | |

DC Electronic Load

PROGRAMMABLE, HIGH PRECISION



SPECIFICATIONS

| Model | PPL-8611C2 | PPL-8612C2 | PPL-8612C3 | PPL-8612B1 | PPL-8613C3 | PPL-8613C4 | PPL-8613B2 | |
|--|-------------------|-------------|-------------|-------------|--------------|-------------|------------|-------------|
| Rated input (0°C~40°C) | | | | | | | | |
| Voltage | 0~150V | 0~150V | 0~150V | 0~500V | 0~150V | 0~150V | 0~500V | |
| Current | 1mA~30A | 1mA~30A | 1mA~60A | 1mA~15A | 1mA~60A | 1mA~120A | 1mA~30A | |
| Power *1 | 150W | 300W | 300W | 300W | 600W | 600W | 600W | |
| MOV@FS current | 1.5V | 0.82V | 1.2V | 3.8V | 0.9V | 1.6V | 4.2V | |
| Voltage measurement | | | | | | | | |
| Low range | 0~30V | 0~30V | 0~30V | 0~30V | 0~30V | 0~30V | 0~30V | |
| Resolution | 1mV | 1mV | 1mV | 1mV | 1mV | 1mV | 1mV | |
| Accuracy | ±(0.05%+0.02%FS) | | | | | | | |
| High range | 0~150V | 0~150V | 0~150V | 0~500V | 0~150V | 0~150V | 0~500V | |
| Resolution | 10mV | 10mV | 10mV | 10mV | 10mV | 10mV | 10mV | |
| Accuracy | ±(0.05%+0.025%FS) | | | | | | | |
| Current measurement | | | | | | | | |
| Low range | 0~3A | 0~3A | 0~6A | 0~1.5A | 0~6A | 0~12A | 0~3A | |
| Resolution | 1mA | 1mA | 1mA | 1mA | 1mA | 1mA | 1mA | |
| Accuracy | ±(0.1%+0.1%FS) | | | | | | | |
| High range | 0~30A | 0~30A | 0~60A | 0~15A | 0~60A | 0~120A | 0~30A | |
| Resolution | 1mA | 1mA | 1mA | 1mA | 1mA | 10mA | 1mA | |
| Accuracy | ±(0.1%+0.15%FS) | | | | | | | |
| Power measurement (Input voltage /current≥10%FS) | | | | | | | | |
| Range | 0~150W | 0~300W | 0~300W | 0~300W | 0~600W | 0~600W | 0~600W | |
| Resolution | P<100W | 1mW | 1mW | 1mW | 1mW | 1mW | 1mW | |
| | P≥100W | 10mW | 10mW | 10mW | 100mW | 100mW | 100mW | |
| Accuracy | 1%+0.1%FS | | | | | | | |
| Current slew rate | | | | | | | | |
| Range | CCH (/us) | 0.1mA~1.5A | 0.1mA~1.5A | 0.1mA~3A | 0.1mA~0.75A | 0.1mA~3A | 0.1mA~6A | 0.1mA~1.5A |
| | CCL (/us)*3 | 0.1mA~0.15A | 0.1mA~0.15A | 0.1mA~0.33A | 0.1mA~0.075A | 0.1mA~0.33A | 0.1mA~0.6A | 0.1mA~0.15A |
| Resolution | | 0.1mA/us | 0.1mA/us | 0.1mA/us | 0.1mA/us | 0.1mA/us | 0.1mA/us | 0.1mA/us |
| Accuracy *4 | | 3%+10us | | | | | | |
| Battery discharge | | | | | | | | |
| Discharge time | | 1s~100h | 1s~100h | 1s~100h | 1s~100h | 1s~100h | 1s~100h | 1s~100h |
| Resolution | | 1s | 1s | 1s | 1s | 1s | 1s | 1s |
| Accuracy | 0.2%+1s | | | | | | | |
| Battery capacity | | 3000Ah | 3000Ah | 6000Ah | 1500Ah | 6000Ah | 12000Ah | 3000Ah |
| Resolution | | 1mAh | 1mAh | 1mAh | 1mAh | 1mAh | 1mAh | 1mAh |
| Accuracy | 0.3%+0.01Ah | | | | | | | |
| Discharge voltage range | | 0.1V~150V | 0.1V~150V | 0.1V~150V | 0.1V~150V | 0.1V~150V | 0.1V~150V | 0.1V~150V |
| Discharge current resolution | | 10mA | 10mA | 10mA | 10mA | 10mA | 10mA | 10mA |
| Short circuit | | | | | | | | |
| CCL | | 3.6A | 3.6A | 7.2A | 1.8A | 7.2A | 14.6A | 3.6A |
| CCH | | 33A | 33A | 66A | 16.5A | 66A | 132A | 33A |
| CV | | 0V | 0V | 0V | 0V | 0V | 0V | 0V |
| VH CRL | | 0.044Ω | 0.027Ω | 0.022Ω | 0.24Ω | 0.015Ω | 0.013Ω | 0.13Ω |
| VH CRM | | 5.6Ω | 5.6Ω | 2.8Ω | 31Ω | 2.8Ω | 1.4Ω | 16Ω |
| VH CRH | | 58Ω | 58Ω | 29Ω | 310Ω | 29Ω | 15Ω | 160Ω |
| VL CRL | | 0.044Ω | 0.027Ω | 0.022Ω | 0.24Ω | 0.015Ω | 0.013Ω | 0.13Ω |
| VL CRM | | 1.1Ω | 1.1Ω | 0.53Ω | 2Ω | 0.53Ω | 0.26Ω | 1.0Ω |
| VL CRH | | 10Ω | 10Ω | 5.3Ω | 20Ω | 5.3Ω | 2.4Ω | 10Ω |
| CPV | | 165W | 315W | 315W | 315W | 630W | 630W | 630W |
| CPC | | 0W | 0W | 0W | 0W | 0W | 0W | 0W |

SPECIFICATIONS

| Model | PPL-8611C2 | PPL-8612C2 | PPL-8612C3 | PPL-8612B1 | PPL-8613C3 | PPL-8613C4 | PPL-8613B2 |
|------------------------|--|------------|------------|------------|--------------|------------|------------|
| Rated input (0°C~40°C) | | | | | | | |
| Voltage | 0~150V | 0~150V | 0~150V | 0~500V | 0~150V | 0~150V | 0~500V |
| Current | 1mA~30A | 1mA~30A | 1mA~60A | 1mA~15A | 1mA~60A | 1mA~120A | 1mA~30A |
| Power *1 | 150W | 300W | 300W | 300W | 600W | 600W | 600W |
| MOV@FS current | 1.5V | 0.82V | 1.2V | 3.8V | 0.9V | 1.6V | 4.2V |
| Max. slew rate | | | | | | | |
| Current | 1.5A /us | 1.5A /us | 3A /us | 0.75A /us | 3A /us | 6A /us | 1.5A /us |
| Voltage | 0.2V /us | 0.2V /us | 0.2V /us | 0.02V /us | 0.2V /us | 0.2V /us | 0.02V /us |
| Open circuit | ≥20kΩ | ≥20kΩ | ≥20kΩ | ≥20kΩ | ≥20kΩ | ≥20kΩ | ≥20kΩ |
| Max. input level | | | | | | | |
| Current | 33A | 33A | 66A | 16.5A | 66A | 132A | 33A |
| Voltage | 175V | 175V | 175V | 550V | 175V | 175V | 550V |
| Ripple & Noise | | | | | | | |
| Current (rms/p-p) | 3mA/30mA | 3mA/30mA | 6mA/60mA | 5mA/50mA | 6mA/60mA | 12mA/120mA | 5mA/50mA |
| Voltage (rms) | 5mV | 5mV | 5mV | 5mV | 5mV | 5mV | 5mV |
| Transient operation | | | | | | | |
| Transient mode | Continuous, Pulse, Toggled | | | | | | |
| Frequency range *5 | 0.01Hz~2kHz | | | | | | |
| High/Low time | 0~99999ms | | | | | | |
| Resolution | 250us | | | | | | |
| Accuracy | 0.2%+10us | | | | | | |
| Rising/Falling time | 250us~99999ms | | | | | | |
| Resolution | 250us | | | | | | |
| Accuracy | 0.2%+10us | | | | | | |
| List Mode | | | | | | | |
| Step time | 10ms~99999s | | | | | | |
| Resolution | 10ms | | | | | | |
| Accuracy | 0.2%+10us | | | | | | |
| No. of steps | 1~50 | | | | | | |
| No. of cycles | 0~65535 | | | | | | |
| Storage | 8 Lists | | | | | | |
| Expanded function | Chain | | | | | | |
| Trigger input | | | | | | | |
| Trigger level | TTL falling edge | | | | | | |
| Trigger pulse width | ≥20us | | | | | | |
| General | | | | | | | |
| Protection | Over current, over voltage, over power, over temperature and reverse voltage protections | | | | | | |
| Interface | RS-232 interface, support SCPI commands, support Labview | | | | | | |
| | Optional RS-232 to USB cable | | | | | | |
| Operating environment | 0°C~40°C, ≤85%RH | | | | | | |
| Storage environment | -10°C~70°C, ≤70%RH | | | | | | |
| Power source | AC110V/220V±10% selectable, 50/60Hz | | | | | | |
| Accessories | Power cord x1, Operation manual x1, RS-232 cable x1 | | | | | | |
| Dimension (WxHxD) | 215x89x412mm | | | | 215x89x507mm | | |
| Weight | 5.2kg | 6.7kg | 6.7kg | 6.7kg | 9kg | 9kg | 9kg |

*1. Maximum continuous power available is derated linearly from 100% of maximum at 40°C, to 75% of maximum at 50°C.

*2. Conductance (S) = 1 / Resistance (Ω).

*3. The set level is 10 times larger than the slew rate in CCL mode.

*4. The actual transition time is defined as the time required for the input to change from 10% to 90% or from 90% to 10% of the programmed excursion.

*5. Transient frequency depends on the time for high/low level and rising/falling edge.

Архангельск (8182)63-90-72

Астана (7172)727-132

Астрахань (8512)99-46-04

Барнаул (3852)73-04-60

Белгород (4722)40-23-64

Брянск (4832)59-03-52

Владивосток (423)249-28-31

Волгоград (844)278-03-48

Вологда (8172)26-41-59

Воронеж (473)204-51-73

Екатеринбург (343)384-55-89

Иваново (4932)77-34-06

Ижевск (3412)26-03-58

Иркутск (395)279-98-46

Казань (843)206-01-48

Калининград (4012)72-03-81

Калуга (4842)92-23-67

Кемерово (3842)65-04-62

Киров (8332)68-02-04

Краснодар (861)203-40-90

Красноярск (391)204-63-61

Курск (4712)77-13-04

Липецк (4742)52-20-81

Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13

Москва (495)268-04-70

Мурманск (8152)59-64-93

Набережные Челны (8552)20-53-41

Нижний Новгород (831)429-08-12

Новокузнецк (3843)20-46-81

Новосибирск (383)227-86-73

Омск (3812)21-46-40

Орел (4862)44-53-42

Оренбург (3532)37-68-04

Пенза (8412)22-31-16

Казахстан (772)734-952-31

Пермь (342)205-81-47

Ростов-на-Дону (863)308-18-15

Рязань (4912)46-61-64

Самара (846)206-03-16

Санкт-Петербург (812)309-46-40

Саратов (845)249-38-78

Севастополь (8692)22-31-93

Симферополь (3652)67-13-56

Смоленск (4812)29-41-54

Сочи (862)225-72-31

Ставрополь (8652)20-65-13

Таджикистан (992)427-82-92-69

Сургут (3462)77-98-35

Тверь (4822)63-31-35

Томск (3822)98-41-53

Тула (4872)74-02-29

Тюмень (3452)66-21-18

Ульяновск (8422)24-23-59

Уфа (347)229-48-12

Хабаровск (4212)92-98-04

Челябинск (351)202-03-61

Череповец (8202)49-02-64

Ярославль (4852)69-52-93