

- Adopts PWM pre-regulation and linear adjustment
- Constant voltage and constant current operations
- Auto CV/CC switch
- Coarse and Fine control for voltage and current
- Over voltage, over current and over temperature protections
- Intelligent cooling fan



SPECIFICATIONS

Constant voltage operation	
Line regulation	≤0.05%+1mV
Load regulation	≤0.1%+5mV
Ripple & Noise	≤10mVrms
Constant current operation	
Line regulation	≤0.05%+10mA
Load regulation	≤0.1%+10mA
Ripple & Noise	≤20mArms
Display	
Accuracy	±(1% reading+1 digit)
General	
Operating environment	0°C ~ 40°C, ≤80%RH
Storage environment	-10°C ~ 70°C, ≤70%RH
Power source	AC110V/220V±10%, 50/60Hz
Accessories	Power cord x1, Operation manual x1

SELECTION GUIDE

Model	Rated Output	Voltage Display	Current Display
S2 chassis: 125x160x260mm (WxHxD), approx.2kg			
SP-1505	0~15V / 0~5A	0.00-9.99-10.0-16.0V	000.-999.mA-1.00-5.10A
SP-1510	0~15V / 0~10A	0.00-9.99-10.0-16.0V	0.00-9.99-10.0-10.1A
SP-1515	0~15V / 0~15A	0.00-9.99-10.0-16.0V	0.00-9.99-10.0-15.1A
SP-1520	0~15V / 0~20A	0.00-9.99-10.0-16.0V	0.00-9.99-10.0-20.1A
SP-3003	0~30V / 0~3A	0.00-9.99-10.0-32.0V	000.-999.mA-1.00-3.10A
SP-3005	0~30V / 0~5A	0.00-9.99-10.0-32.0V	000.-999.mA-1.00-5.10A
SP-3010	0~30V / 0~10A	0.00-9.99-10.0-32.0V	0.00-9.99-10.0-10.1A
SP-6002	0~60V / 0~2A	00.0-62.0V	000.-999.mA-1.00-2.10A
SP-6003	0~60V / 0~3A	00.0-62.0V	000.-999.mA-1.00-3.10A
SP-6005	0~60V / 0~5A	00.0-62.0V	000.-999.mA-1.00-5.10A
SP-1001	0~100V / 0~1A	00.0-99.9-100-102V	000.-999.mA-1.00-1.10A
SP-1002	0~100V / 0~2A	00.0-99.9-100-102V	000.-999.mA-1.00-2.10A
SP-1003	0~100V / 0~3A	00.0-99.9-100-102V	000.-999.mA-1.00-3.10A
SP-12001	0~120V / 0~1A	00.0-99.9-100-122V	000.-999.mA-1.00-1.10A
SP-12002	0~120V / 0~2A	00.0-99.9-100-122V	000.-999.mA-1.00-2.10A

Архангельск (8182)63-90-72
 Астана (7172)727-132
 Астрахань (8512)99-46-04
 Барнаул (3852)73-04-60
 Белгород (4722)40-23-64
 Брянск (4832)59-03-52
 Владивосток (423)249-28-31
 Волгоград (844)278-03-48
 Вологда (8172)26-41-59
 Воронеж (473)204-51-73
 Екатеринбург (343)384-55-89
 Иваново (4932)77-34-06

Ижевск (3412)26-03-58
 Иркутск (395)279-98-46
 Казань (843)206-01-48
 Калининград (4012)72-03-81
 Калуга (4842)92-23-67
 Кемерово (3842)65-04-62
 Киров (8332)68-02-04
 Краснодар (861)203-40-90
 Красноярск (391)204-63-61
 Курск (4712)77-13-04
 Липецк (4742)52-20-81
 Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
 Москва (495)268-04-70
 Мурманск (8152)59-64-93
 Набережные Челны (8552)20-53-41
 Нижний Новгород (831)429-08-12
 Новокузнецк (3843)20-46-81
 Новосибирск (383)227-86-73
 Омск (3812)21-46-40
 Орел (4862)44-53-42
 Оренбург (3532)37-68-04
 Пенза (8412)22-31-16
 Казахстан (772)734-952-31

Пермь (342)205-81-47
 Ростов-на-Дону (863)308-18-15
 Рязань (4912)46-61-64
 Самара (846)206-03-16
 Санкт-Петербург (812)309-46-40
 Саратов (845)249-38-78
 Севастополь (8692)22-31-93
 Симферополь (3652)67-13-56
 Смоленск (4812)29-41-54
 Сочи (862)225-72-31
 Ставрополь (8652)20-65-13
 Таджикистан (992)427-82-92-69

Сургут (3462)77-98-35
 Тверь (4822)63-31-35
 Томск (3822)98-41-53
 Тула (4872)74-02-29
 Тюмень (3452)66-21-18
 Ульяновск (8422)24-23-59
 Уфа (347)229-48-12
 Хабаровск (4212)92-98-04
 Челябинск (351)202-03-61
 Череповец (8202)49-02-64
 Ярославль (4852)69-52-93