

Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06

Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Казахстан (772)734-952-31

Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Таджикистан (992)427-82-92-69

Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

<https://twintex.nt-rt.ru/> || ttw@nt-rt.ru

Dual Output Linear DC Power Supplies



Product No : TP2000E__Series

Product Description

The TP2000E series are low-cost linear DC power supplies with 2 channels, 180W to 300W output. In constant voltage and current operations, the power supply provides high regulation and low ripple & noise. Auto series and parallel operations double output voltage and current. The TP2000E series are widely used in applications of powering operational amplifier, push pull stages, logic circuit and definition systems.

- ★ Two independent adjustable outputs 0~30V/0~3A/5A x2
- ★ Constant voltage and constant current operations
- ★ Low ripple and noise, low temperature drift
- ★ Auto Series and Parallel tracking operations
- ★ High efficiency, high power density
- ★ Over load and reverse polarity protections
- ★ Dual-color four digital panel meters

Model		TP-2303E	TP-2305E
Output		0~30V/0~3A x2	0~30V/0~5A x2
Constant voltage operation			
Line regulation		≤0.01%+3mV	
Load regulation		≤0.01%+3mV	≤0.02%+5mV
Ripple & Noise		≤1mVrms	≤2mVrms
Constant current operation			
Line regulation		≤0.2%+3mA	
Load regulation		≤0.2%+3mA	≤0.2%+5mA
Ripple & Noise		≤3mArms	≤6mArms
Tracking operation			
Parallel	Line regulation	≤0.01%+3mV	
	Load regulation	≤0.01%+3mV	≤0.02%+5mV
Series	Line regulation	≤0.01%+5mV	
	Load regulation	≤300mV	
	Tracking error	≤0.5%+10mV of the master, no load (with load, add load regulation≤300mV)	
Display			
Voltmeter		3 digits LED display	
Ammeter		3 digits LED display	
Resolution		100mV/10mA	
Accuracy	Voltage	±(0.5% reading+2digits)	
	Current	±(1% reading+2digits)	
Protection		Over load and reverse polarity protections	
Power source		AC110V, AC220V or AC110V/220V±10%, 50/60Hz	
Operating environment		0°C~40°C, ≤80%RH	
Storage environment		-10°C~70°C, ≤70%RH	
Accessories		Power cord x1, Operation manual x1	

Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06

Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Казахстан (772)734-952-31

Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Орел (4862)44-53-42
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Таджикистан (992)427-82-92-69

Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93