

Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06

Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Казахстан (772)734-952-31

Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Таджикистан (992)427-82-92-69

Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

<https://twintex.nt-rt.ru/> || ttw@nt-rt.ru

Triple Output Linear DC Power Supply



Product No : TP2000K__Series

Product Description

The TP2000K series are linear DC power supplies with 3 channels, 195W to 315W output. In constant voltage and current operations, the power supply provides high regulation and low ripple & noise. Auto series and parallel operations double output voltage and current. The output ON/OFF control and preset voltage & current function protect the power supply and related loads from unexpected damages. The TP2000K series are widely used in applications of powering operational amplifier, push pull stages, logic circuit and definition systems.

- ★ Two independent adjustable outputs 0~30V/0~3A/5A x2, one fixed output 5V/3A x1
- ★ Constant voltage and constant current operations
- ★ Low ripple and noise, low temperature drift
- ★ Auto Series and Parallel tracking operations
- ★ Output ON/OFF control
- ★ High efficiency, high power density
- ★ Over load and reverse polarity protections
- ★ Dual-color four digital panel meters

Model		TP-2303K	TP-2305K
Output		0~30V/0~3A x2, fixed 5V/3A	0~30V/0~5A x2, fixed 5V/3A
Constant voltage operation			
Line regulation		≤0.01%+3mV	
Load regulation		≤0.01%+3mV	≤0.02%+5mV
Ripple & Noise		≤1mVrms	≤2mVrms
Constant current operation			
Line regulation		≤0.2%+3mA	
Load regulation		≤0.2%+3mA	≤0.2%+5mA
Ripple & Noise		≤3mArms	≤6mArms
Tracking operation			
Parallel	Line regulation	≤0.01%+3mV	
	Load regulation	≤0.01%+3mV	≤0.02%+5mV
Series	Line regulation	≤0.01%+5mV	
	Load regulation	≤300mV	
	Tracking error	≤0.5%+10mV of the master, no load (with load, add load regulation≤300mV)	
Fixed output			
Output voltage		5V±0.25V	
Output current		3A	
Line regulation		≤25mV	
Load regulation		≤25mV	
Ripple & noise		≤2.0mVrms	
Protection		Over load and reverse polarity protections	
Display			
Voltmeter		3 digits LED display	
Ammeter		3 digits LED display	
Resolution		100mV/10mA	
Accuracy	Voltage	±(0.5% reading+2digits)	
	Current	±(1% reading+2digits)	
Protection		Over load and reverse polarity protections	
Power source		AC110V, AC220V or AC110V/220V±10%, 50/60Hz	
Operating environment		0°C~40°C, ≤80%RH	
Storage environment		-10°C~70°C, ≤70%RH	
Accessories		Power cord x1, Operation manual x1	

Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06

Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Казахстан (772)734-952-31

Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Таджикистан (992)427-82-92-69

Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

<https://twintex.nt-rt.ru/> || ttw@nt-rt.ru