

FEATURES

TP4000N SERIES

- Four independent outputs
- Constant voltage and constant current operations
- Auto CV and CC switch
- Low ripple and noise, low temperature drift
- Auto Series and Parallel tracking operations
- Output ON/OFF control
- Preset function, setting of voltage and current with output open circuit
- High efficiency, high power density
- Over load and reverse polarity protections
- Dual-color four digital panel meters
- SMD PCB, high quality, high reliability



0~30V / 0~3A x2
0~30V / 0~5A x2
0~50V / 0~3A x2
AUX.:
2.2~15V/1A x2



SPECIFICATIONS

| | | |
|----------------------------|---|---|
| Independent operation | Constant voltage | Constant current |
| Line regulation | ≤0.01%+3mV | ≤0.2%+3mA |
| Load regulation | ≤0.01%+3mV (I≤3A); ≤0.02%+5mV (I>3A) | ≤0.2%+3mA (I≤3A); ≤0.2%+5mA (I>3A) |
| Ripple & Noise (5Hz~1MHz) | ≤1mVrms (I≤3A); ≤2mVrms (I>3A) | ≤3mArms (I≤3A); ≤6mArms (I>3A) |
| Tracking operation | | |
| Parallel | Line regulation | ≤0.01%+3mV |
| | Load regulation | ≤0.02%+5mV |
| Series | Line regulation | ≤0.01%+5mV |
| | Load regulation | ≤300mV |
| | Tracking error | ≤0.5%+10mV of the master, no load (with load, add load regulation ≤300mV) |
| Auxiliary output (CH3/CH4) | | |
| Load regulation | ≤25mV @110/220VAC rated input | |
| Ripple & noise (5Hz~1MHz) | ≤2mVrms | |
| Display | | |
| Accuracy | Real voltage and current output: ±(1% reading+2 digits) | |
| | Preset voltage and current: ±(1% reading+8 digits) | |
| General | | |
| Operating environment | 0°C~40°C, ≤80%RH | |
| Storage environment | -10°C~70°C, ≤70%RH | |
| Power source | AC110V/220V±10%, 50/60Hz | |
| Accessories | Power cord x1, Operation manual x1 | |

SELECTION GUIDE

| Model | TP-4303N | TP-4305N | TP-4503N |
|--------------------|---------------|---------------|---------------|
| Output voltage | 0~30V x2 | 0~30V x2 | 0~50V x2 |
| Output current | 0~3A x2 | 0~5A x2 | 0~3A x2 |
| Auxiliary output | 2.2~15V/1A x2 | 2.2~15V/1A x2 | 2.2~15V/1A x2 |
| Preset V&I | ✓ | ✓ | ✓ |
| Output ON/OFF | ✓ | ✓ | ✓ |
| Tracking operation | ✓ | ✓ | ✓ |
| Dimension (WxHxD) | 255x155x310mm | | |
| Weight | 8.5kg | 10kg | 10kg |

Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06

Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Казахстан (772)734-952-31

Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Таджикистан (992)427-82-92-69

Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8020)49-02-64
Ярославль (4852)69-52-93