

PCL SERIES

0~6V~600V
0~1.2A~300A
600W~6000W



FEATURES

- Max. rated output 600W, 1200W, 2400W, 3000W and 6000W
- Max. rated voltage from 6V to 600V
- Max. rated current from 1.2A to 300A
- Adopting ZVZCS PWM technology, high efficiency and high stability
- 4 digits LED display for voltage and current
- Constant voltage and constant current operations
- Auto CV/CC switch
- Low ripple, high stability
- Panel lock and output ON/OFF function
- Preset function, setting of voltage and current with output open circuit
- Over voltage, over temperature, under voltage and current limit protections
- Built into 19-inch standard chassis, easy use in cabinet installation and auto test system integration
- Thermostatic control fan, low noise
- Multiple programming interfaces: RS-232, RS-485 and RS-422
- Support ModBus-RTU commands

Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06

Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Казахстан (772)734-952-31

Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Таджикистан (992)427-82-92-69

Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

<https://twintex.nt-rt.ru/> || ttw@nt-rt.ru

Switching Mode DC Power Supply

PROGRAMMABLE, HIGH POWER

SPECIFICATIONS

Output capacity	600W~6000W
Working mode	ZVZCS PWM
Output	
Output voltage	DC 0~100% full range adjustable
Output current	DC 0~100% full range adjustable
O.V.P. range	DC 0.1V~105% rated output
Display	
Voltmeter	4 digits LED display
Ammeter	4 digits LED display
Voltage resolution	0.000-9.999V; 00.00-99.99V; 000.0-999.9V
Current resolution	0.000-9.999A; 00.00-99.99A; 000.0-999.9A
Voltage accuracy	≤0.2%+2LSB
Current accuracy	≤0.5%+2LSB
General	
Protection	Adjustable OVP protection with limit of 105% rated output voltage Built-in OTP protection with heat sink temperature limit of 50°C±5%. The output will be shut down when OTP is activated. Built-in UVP protection with limit of 165Vac. The output will be shut down when UVP is activated.
Panel lock	Provided
Interface	RS-232 / RS-485 / RS-422 interface, support ModBus-RTU commands
Cooling method	Cooling fan
Operating environment	0°C~40°C, <80%RH
Storage environment	-10°C~70°C, <80%RH
Power source	Single phase AC220V±10%, 50/60Hz for 600W, 1200W, 2400W and 3000W models Three phase AC380V±10%, 50/60Hz for 6000W models
Input module	Power socket or terminal block
Accessories	Power cord x1, Operation manual x1, RS-232 cable x1
Dimension (WxHxD)	213x88x340mm for 600W models 482x88x460mm for 1200W, 2400W and 3000W models 482x132x535mm for 6000W models
Weight	Approx. 5kg for 600W models Approx. 11~15kg for 1200W, 2400W and 3000W models Approx. 35kg for 6000W models

SELECTION GUIDE

Model	PCL600-1H	PCL600-150	PCL600-2H	PCL600-3H	PCL600-4H	PCL600-5H
Output voltage	0~100V	0~150V	0~200V	0~300V	0~400V	0~500V
Output current	0~6A	0~4A	0~3A	0~2A	0~1.5A	0~1.2A
O.V.P. range	0.1~105V	0.1~157.5V	0.1~210V	0.1~315V	0.1~420V	0.1~525V
Line regulation	CV≤0.1%+2LSB, CC≤0.1%+2LSB					
Load regulation	CV≤0.1%+2LSB, CC≤0.2%+2LSB					
Ripple & Noise	≤100mV	≤100mV	≤200mV	≤200mV	≤200mV	≤200mV
Setting resolution	100mV/1mA					
Reading resolution	100mV/1mA					

Switching Mode DC Power Supply

PROGRAMMABLE, HIGH POWER



SELECTION GUIDE

Model	PCL1200-6	PCL1200-12	PCL1200-15	PCL1200-30	PCL1200-60	PCL1200-1H	PCL1200-150	PCL1200-2H
Output voltage	0~6V	0~12V	0~15V	0~30V	0~60V	0~100V	0~150V	0~200V
Output current	0~200A	0~100A	0~80A	0~40A	0~20A	0~12A	0~8A	0~6A
O.V.P. range	0.1~6.3V	0.1~12.6V	0.1~15.75V	0.1~31.5V	0.1~63V	0.1~105V	0.1~157.5V	0.1~210V
Line regulation	CV≤0.1%+2LSB, CC≤0.1%+2LSB							
Load regulation	CV≤0.2%+2LSB			CV≤0.1%+2LSB				
	CC≤0.2%+2LSB			CC≤0.1%+2LSB				
Ripple & Noise	≤50mV	≤50mV	≤50mV	≤50mV	≤50mV	≤100mV	≤100mV	≤100mV
Setting resolution	1mV/100mA	10mV/100mA	10mV/10mA	10mV/10mA	10mV/10mA	100mV/10mA	100mV/1mA	100mV/1mA
Reading resolution	1mV/100mA	10mV/100mA	10mV/10mA	10mV/10mA	10mV/10mA	100mV/10mA	100mV/1mA	100mV/1mA

Model	PCL1200-3H	PCL1200-4H	PCL1200-5H	PCL1200-6H	PCL2400-12	PCL2400-20	PCL2400-30	PCL2400-40
Output voltage	0~300V	0~400V	0~500V	0~600V	0~12V	0~20V	0~30V	0~40V
Output current	0~4A	0~3A	0~2.4A	0~2A	0~200A	0~120A	0~80A	0~60A
O.V.P. range	0.1~315V	0.1~420V	0.1~525V	0.1~630V	0.1~12.6V	0.1~21V	0.1~31.5V	0.1~42V
Line regulation	CV≤0.1%+2LSB, CC≤0.1%+2LSB							
Load regulation	CV≤0.1%+2LSB, CC≤0.1%+2LSB							
Ripple & Noise	≤100mV	≤100mV	≤200mV	≤200mV	≤100mV	≤100mV	≤100mV	≤100mV
Setting resolution	100mV/1mA	100mV/1mA	100mV/1mA	100mV/1mA	10mV/100mA	10mV/100mA	10mV/10mA	10mV/10mA
Reading resolution	100mV/1mA	100mV/1mA	100mV/1mA	100mV/1mA	10mV/100mA	10mV/100mA	10mV/10mA	10mV/10mA

Model	PCL2400-60	PCL2400-1H	PCL2400-150	PCL2400-2H	PCL2400-3H	PCL2400-4H	PCL2400-50H	PCL2400-6H
Output voltage	0~60V	0~100V	0~150V	0~200V	0~300V	0~400V	0~500V	0~600V
Output current	0~40A	0~24A	0~16A	0~12A	0~8A	0~6A	0~4.8A	0~4A
O.V.P. range	0.1~63V	0.1~105V	0.1~157.5V	0.1~210V	0.1~315V	0.1~420V	0.1~525V	0.1~630V
Line regulation	CV≤0.1%+2LSB, CC≤0.1%+2LSB							
Load regulation	CV≤0.1%+2LSB, CC≤0.1%+2LSB							
Ripple & Noise	≤100mV	≤100mV	≤100mV	≤100mV	≤200mV	≤200mV	≤200mV	≤200mV
Setting resolution	10mV/10mA	100mV/10mA	100mV/10mA	100mV/10mA	100mV/1mA	100mV/1mA	100mV/1mA	100mV/1mA
Reading resolution	10mV/10mA	100mV/10mA	100mV/10mA	100mV/10mA	100mV/1mA	100mV/1mA	100mV/1mA	100mV/1mA

Model	PCL3000-20	PCL3000-30	PCL3000-40	PCL3000-60	PCL3000-1H	PCL3000-150	PCL3000-2H	PCL3000-3H	PCL3000-4H	PCL3000-5H
Output voltage	0~20V	0~30V	0~40V	0~60V	0~100V	0~150V	0~200V	0~300V	0~400V	0~500V
Output current	0~150A	0~100A	0~75A	0~50A	0~30A	0~20A	0~15A	0~10A	0~7.5A	0~6A
O.V.P. range	0.1~21V	0.1~31.5V	0.1~42V	0.1~63V	0.1~105V	0.1~157.5V	0.1~210V	0.1~315V	0.1~420V	0.1~525V
Line regulation	CV≤0.1%+2LSB, CC≤0.1%+2LSB									
Load regulation	CV≤0.1%+2LSB, CC≤0.1%+2LSB									
Ripple & Noise	≤100mV	≤100mV	≤100mV	≤100mV	≤100mV	≤200mV	≤200mV	≤200mV	≤200mV	≤200mV
Setting resolution	10mV/100mA	10mV/100mA	10mV/10mA	10mV/10mA	100mV/10mA	100mV/10mA	100mV/10mA	100mV/10mA	100mV/1mA	100mV/1mA
Reading resolution	10mV/100mA	10mV/100mA	10mV/10mA	10mV/10mA	100mV/10mA	100mV/10mA	100mV/10mA	100mV/10mA	100mV/1mA	100mV/1mA

Архангельск (8182)63-90-72
 Астана (7172)727-132
 Астрахань (8512)99-46-04
 Барнаул (3852)73-04-60
 Белгород (4722)40-23-64
 Брянск (4832)59-03-52
 Владивосток (423)249-28-31
 Волгоград (844)278-03-48
 Вологда (8172)26-41-59
 Воронеж (473)204-51-73
 Екатеринбург (343)384-55-89
 Иваново (4932)77-34-06

Ижевск (3412)26-03-58
 Иркутск (395)279-98-46
 Казань (843)206-01-48
 Калининград (4012)72-03-81
 Калуга (4842)92-23-67
 Кемерово (3842)65-04-62
 Киров (8332)68-02-04
 Краснодар (861)203-40-90
 Красноярск (391)204-63-61
 Курск (4712)77-13-04
 Липецк (4742)52-20-81
 Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
 Москва (495)268-04-70
 Мурманск (8152)59-64-93
 Набережные Челны (8552)20-53-41
 Нижний Новгород (831)429-08-12
 Новокузнецк (3843)20-46-81
 Новосибирск (383)227-86-73
 Омск (3812)21-46-40
 Орел (4862)44-53-42
 Оренбург (3532)37-68-04
 Пенза (8412)22-31-16
 Казахстан (772)734-952-31

Пермь (342)205-81-47
 Ростов-на-Дону (863)308-18-15
 Рязань (4912)46-61-64
 Самара (846)206-03-16
 Санкт-Петербург (812)309-46-40
 Саратов (845)249-38-78
 Севастополь (8692)22-31-93
 Симферополь (3652)67-13-56
 Смоленск (4812)29-41-54
 Сочи (862)225-72-31
 Ставрополь (8652)20-65-13
 Таджикистан (992)427-82-92-69

Сургут (3462)77-98-35
 Тверь (4822)63-31-35
 Томск (3822)98-41-53
 Тула (4872)74-02-29
 Тюмень (3452)66-21-18
 Ульяновск (8422)24-23-59
 Уфа (347)229-48-12
 Хабаровск (4212)92-98-04
 Челябинск (351)202-03-61
 Череповец (8202)49-02-64
 Ярославль (4852)69-52-93

<https://twintex.nt-rt.ru/> || ttw@nt-rt.ru